


# Dot Graphic VFD Module

**CU20049-KTW220A**

- q 4 Lines of 20 Characters 9mm High
- q High Speed Parallel/TTL Serial Interface
- q Operating Temp -40°C to +85°C
- q Single 5V Supply
- q High Brightness Blue Green Display
- q ASCII, Katakana & Extended Character Font
- q 16 User Definable Character RAM

The module includes the Vacuum Fluorescent Display glass, driver and micro-controller ICs with refresh RAM, character generator and interface logic. The high speed 8 bit parallel interface is 5V CMOS compatible suitable for connection to a host CPU bus. The asynchronous serial interface accepts baud rates up to 19,200 with or without parity. Two character font tables can be hardware or software selected. User defined characters and many control commands are available.



Dimensions in mm & subject to tolerances. Mounting holes 3.5mm dia.

## ELECTRICAL SPECIFICATION

Parameter	Symbol	Value	Condition
Power Supply Voltage	Vcc	5.0VDC +/- 5%	GND=0V
Power Supply Current	Icc	1100mA typ.	Vcc=5V
Logic High Input	VIH	2.0VDC min.	Vcc=5V
Logic Low Input	VIL	0.8VDC max.	Vcc=5V
Logic High Output	VOH	2.4VDC min.	IOH = -2.0mA
Logic Low Output	VOL	0.5VDC max.	IOL = 2.0mA

The power on rise time should be less than 50ms. The inrush current at power on can be 2 x Icc.

## OPTICAL and ENVIRONMENTAL SPECIFICATIONS

Parameter	Value
Character Size/Pitch (XxY mm)	6.4 x 9.1/8.3 x 11.1
Dot Size/Pitch (XxY mm)	1.0 x 1.0/1.35 x 1.35
Luminance	350 cd/m² min.
Colour of Illumination	Blue-Green (Filter for colours)
Operating Temperature	-40°C to +85°C
Storage Temperature	-40°C to +85°C
Operating Humidity (non condensing)	20 to 80% RH @ 25°C

## SOFTWARE COMMANDS

Instruction	D0-D7	Instruction	D0-D7
Back Space	08H	Katakana Font	19H
Horizontal Tab	09H	Euro Currency Mark	1AH
Line Feed	0AH	Escape	1BH
Form Feed	0CH	Send User Font	+43H
Carriage Return	0DH	Position cursor	+48H
Clear Display	0EH	Software Reset	+49H
Increment Write Mode	11H	Luminance	+4CH
Vertical Scroll Mode	12H	Flickerless Write	+53H
5x7 Block Cursor On	15H	Cursor Blink Speed	+54H
Cursor Off	16H	Character Data	20H-FFH
International Font	18H	User Character Data	00H-FFH

## TIMING PARAMETERS (min)

Data Set Up To Write	50ns	Subject to change without notice.
Write Pulse Width	100ns	Detailed specification on request.
Hold After Write	10ns	IUK Doc Ref: 5043 Iss:5 28Feb07

CHARACTER FONTS			
International Font			
Additional Katakana Font			
00	01	02	03
04	05	06	07
08	09	0A	0B
0C	0D	0E	0F
0G	0H	0I	0J
0K	0L	0M	0N
0P	0Q	0R	0S
0T	0U	0V	0W
0X	0Y	0Z	0A'
0B'	0C'	0D'	0E'
0F'	0G'	0H'	0I'
0J'	0K'	0L'	0M'
0N'	0O'	0P'	0Q'
0S'	0T'	0U'	0V'
0W'	0X'	0Y'	0Z'

International font location ADH (when Euro currency mark is enabled)

## IDC DATA CONNECTOR

Pin	Sig	Pin	Sig
1	D7	9	/WR
2	D6	10	/CS
3	D5	11	SIN/TEST
4	D4	12	BUSY
5	D3	13	GND (0V)
6	D2	14	GND (0V)
7	D1	15	Vcc (5V)
8	D0	16	Vcc (5V)

## 3 PIN POWER CONNECTOR

Pin	Sig
1	Vcc (5V)
2	SIN/TEST
3	GND (0V)

Mates with AMP171822-3  
Defaults: 19200, Even parity,  
International Font.  
Hold SIN/Test to Gnd at Power-up  
for Self-Test mode.

## PCB JUMPERS (O)OPEN (L)INK

Baud	J2	J1	J0
19200	O	O	O
9600	O	O	L
4800	O	L	O
2400	O	L	L
1200	L	O	O
Parity	J4	J3	
EVEN	O	O	
ODD	O	L	
NONE	L	L	O
Font	JA		
International	O		
Katakana	L		

Noritake Sales Office Tel Nos  
Nagoya Japan: +81 (0)52-561-9867  
Canada: +1-416-291-2946  
Chicago USA: +1-847-439-9020  
Munchen (D): +49 (0)89-3214-290  
Iron UK: +44 (0)1493 601144  
Rest Europe: +49 (0)61-0520-9220  
[www.noritake-itron.com](http://www.noritake-itron.com)

## SOFTWARE COMMANDS

Busy Time 25uS unless stated below

Instruction +busy time	Data Format	Description																																																																																											
Backspace	08H	Moves the cursor left by one character. If the cursor is at the left end of the display the cursor moves to the right end of the line above. If the cursor is at the left end of the top line no cursor movement is made.																																																																																											
Horizontal Tab 75us on scroll	09H	Moves the cursor right by one character. If the cursor is at the right end of the display the cursor moves to the left end of the line below. If the cursor is at the right end of the bottom line the action depends on the write mode currently selected. In DC1 mode the cursor moves to the left end of the top line. In DC2 mode the entire display contents is scrolled up by one line, the bottom line is cleared and the cursor moves to the left end of the bottom line.																																																																																											
Line Feed 75us on scroll	0AH	Moves the cursor down by one line. If the cursor is at the bottom of the display the action depends on the write mode currently selected. In DC1 mode the cursor moves to the top line. In DC2 mode the entire contents of the display is scrolled up by one line and no cursor movement is made.																																																																																											
Form Feed	0CH	Moves the cursor to the top left end of the display.																																																																																											
Carriage Return	0DH	Moves the cursor to the left end of the current line.																																																																																											
Clear 75us	0EH	Clear all displayed characters. No cursor movement is made.																																																																																											
Overwrite mode (DC1)	11H	Specifies character overwrite mode. (default)																																																																																											
Vertical scroll mode (DC2)	12H	Specifies vertical scroll mode.																																																																																											
Cursor off (DC4)	14H	No cursor is displayed. (default)																																																																																											
Cursor on (DC5)	15H	A blinking full block is displayed at the cursor position. The blink rate can be specified using the Blink Speed Control command.																																																																																											
Cursor off (DC6)	16H	No cursor is displayed.																																																																																											
Cursor off (DC7)	17H	No cursor is displayed.																																																																																											
International Font	18H	All subsequent characters displayed will be from the International font. This font can also be selected as the default by using the JA hardware jumper link (OPEN).																																																																																											
KATAKANA Font	19H	All subsequent character displayed will be from the KATAKANA font. This font can also be selected as the default by using the JA hardware jumper link (LINKED).																																																																																											
Euro Symbol 75us on scroll	1AH	This command enables the Euro currency mark at location ADH in the International font. Sending the International Font command (or after a reset) restores the character at location ADH to a blank (this is the default condition). This will affect any existing ADH characters already on the display.																																																																																											
User Defined Font	1BH + 43H + character code + data byte 1 + data byte 2 + data byte 3 + data byte 4 + data byte 5	<p>Define a user character. Up to 16 user characters can be defined and stored by the module. The specified character code can be 00H – FFH. Command codes can be overwritten with a UDF so be aware that doing so will disable that command. All UDF's are lost on power off or reset. If more than 16 UDF's are defined the older definitions are overwritten.</p> <table border="1" style="margin-left: auto; margin-right: auto;"> <tr> <td colspan="8">Bit / Byte assignment</td> </tr> <tr> <td></td><td>7</td><td>6</td><td>5</td><td>4</td><td>3</td><td>2</td><td>1 0</td> </tr> <tr> <td>Byte 1</td><td>P8</td><td>P7</td><td>P6</td><td>P5</td><td>P4</td><td>P3</td><td>P2 P1</td> </tr> <tr> <td>Byte 2</td><td>P16</td><td>P15</td><td>P14</td><td>P13</td><td>P12</td><td>P11</td><td>P10 P9</td> </tr> <tr> <td>Byte 3</td><td>P24</td><td>P23</td><td>P22</td><td>P21</td><td>P20</td><td>P19</td><td>P18 P17</td> </tr> <tr> <td>Byte 4</td><td>P32</td><td>P31</td><td>P30</td><td>P29</td><td>P28</td><td>P27</td><td>P26 P25</td> </tr> <tr> <td>Byte 5</td><td>-</td><td>-</td><td>-</td><td>-</td><td>-</td><td>P35</td><td>P34 P33</td> </tr> </table> <p style="text-align: right;">Dot assignment</p> <table border="1" style="margin-left: auto; margin-right: auto;"> <tr> <td>P1</td><td>P2</td><td>P3</td><td>P4</td><td>P5</td> </tr> <tr> <td>P6</td><td>P7</td><td>P8</td><td>P9</td><td>P10</td> </tr> <tr> <td>P11</td><td>P12</td><td>P13</td><td>P14</td><td>P15</td> </tr> <tr> <td>P16</td><td>P17</td><td>P18</td><td>P19</td><td>P20</td> </tr> <tr> <td>P21</td><td>P22</td><td>P23</td><td>P24</td><td>P25</td> </tr> <tr> <td>P26</td><td>P27</td><td>P28</td><td>P29</td><td>P30</td> </tr> <tr> <td>P31</td><td>P32</td><td>P33</td><td>P34</td><td>P35</td> </tr> </table>	Bit / Byte assignment									7	6	5	4	3	2	1 0	Byte 1	P8	P7	P6	P5	P4	P3	P2 P1	Byte 2	P16	P15	P14	P13	P12	P11	P10 P9	Byte 3	P24	P23	P22	P21	P20	P19	P18 P17	Byte 4	P32	P31	P30	P29	P28	P27	P26 P25	Byte 5	-	-	-	-	-	P35	P34 P33	P1	P2	P3	P4	P5	P6	P7	P8	P9	P10	P11	P12	P13	P14	P15	P16	P17	P18	P19	P20	P21	P22	P23	P24	P25	P26	P27	P28	P29	P30	P31	P32	P33	P34	P35
Bit / Byte assignment																																																																																													
	7	6	5	4	3	2	1 0																																																																																						
Byte 1	P8	P7	P6	P5	P4	P3	P2 P1																																																																																						
Byte 2	P16	P15	P14	P13	P12	P11	P10 P9																																																																																						
Byte 3	P24	P23	P22	P21	P20	P19	P18 P17																																																																																						
Byte 4	P32	P31	P30	P29	P28	P27	P26 P25																																																																																						
Byte 5	-	-	-	-	-	P35	P34 P33																																																																																						
P1	P2	P3	P4	P5																																																																																									
P6	P7	P8	P9	P10																																																																																									
P11	P12	P13	P14	P15																																																																																									
P16	P17	P18	P19	P20																																																																																									
P21	P22	P23	P24	P25																																																																																									
P26	P27	P28	P29	P30																																																																																									
P31	P32	P33	P34	P35																																																																																									
Cursor Moving	1BH + 48H + position	The cursor is moved to the specified position. The relationship between the position value and the display is as follows:-																																																																																											
Luminance	1BH + 4CH + luminance	The display luminance can be set to one of 4 levels. luminance = 00H – 3FH specifies 25% luminance = 40H – 7FH specifies 50% luminance = 80H – BFH specifies 75% luminance = C0H – FFH specifies 100% (default)																																																																																											
Flickerless Writing Mode	1BH + 53H	Set flickerless write mode. By default, priority is given to data communication and display flicker can occur if data is sent to the display continuously. If flickerless writing mode is specified, priority is given to display refresh to avoid possible flicker. Command and data busy times will be up to 220us longer when this mode is set.																																																																																											
Blink Speed Control	1BH + 54H + speed	The blink rate of the cursor can be specified. Rate = speed x 30ms. (default=14H)																																																																																											
Initialise 105 us	1BH + 49H	Clear the display, erase any defined characters, set the cursor position to the top left of the display and reset all settings to defaults.																																																																																											
Character Write 40us on scroll	20H – FFH	Display the specified character from the currently selected font (or UDF is defined) at the current cursor position. After the character is written to the display a horizontal tab automatically follows.																																																																																											